

















# POWER PS SONIC®

## SLA Batteries PS, PSG, PSH and PG Series Terminal Details

<b>F1</b>  <b>FASTON</b> 0.187" x 0.032" quick disconnect tabs.	<b>WL</b> <b>INSULATED WIRE LEADS</b> <ul style="list-style-type: none"> <li>Molex Housing 5264-02 &amp; 5263-PBT plug on PS-605</li> <li>AMP Housing 1-480318-0 &amp; 8116-1 on PS-1208</li> </ul>	<b>NB1</b>  Torque: 2.0~3.0 Nxm	<b>B, T6</b> <b>THREADED INSERT - 6mm STUD</b>  Torque: 3.9~5.4 Nxm
<b>F2</b>  <b>FASTON</b> 0.250" x 0.032" quick disconnect tabs.	<b>PC</b> <b>PRESSURE CONTACTS</b>	<b>NB2</b>  Torque: 3.9~5.4 Nxm	<b>T8</b> <b>THREADED INSERT - 6mm STUD</b>  Torque: 3.9~5.4 Nxm
<b>FP</b>  <b>FASTON POLARIZED</b> Positive: "F2", Negative: "F1"	<b>TH</b>  <b>TOY BATTERY CONNECTORS</b> H-connector PS-6120 TH	<b>NB3</b>  Torque: 3.9~5.4 Nxm	<b>T11</b> <b>THREADED INSERT - 8mm STUD</b>  Torque: 11.0~14.7 Nxm
<b>F1/0</b>  Dimensions: 6, 4.8, 21, ±0.6	<b>TS</b>  <b>TOY BATTERY CONNECTORS</b> S-connector PS-6120 TS	<b>NB4</b>  Torque: 3.9~5.4 Nxm	<b>T12</b> <b>THREADED INSERT - 5mm STUD</b>  Torque: 2.0~3.0 Nxm
<b>SP</b>  <b>SPRING TERMINALS</b> Fully collapsible positive and negative contacts	<b>U</b>  Positive: 17.4, 18, 22, 19 Negative: 15.9, 18, 22, 17.5 Torque: 11.0~14.7 Nxm		